

# MINI PC K6-F13H

Intel Celeron N3150



<b>CPU</b>	Intel Celeron N3150 1.60-2.08GHz
<b>Cores/Threads</b>	4 Cores / 4 Threads
<b>Cache</b>	2MB L2 Cache
<b>TDP</b>	6W
<b>Architecture</b>	Products formerly Braswell
<b>Memory</b>	1*DDR3L slot,max support 8GB
<b>Storage</b>	SSD (mSATA)
	Optional HDD (the motherboard supports the expansion of a 2.5-inch hard drive) The shell does not support HDD expansion
<b>Audio Card</b>	HD Audio realtek ALC 662
<b>Graphics</b>	Intel®HD Graphics for Intel® Celeron® Processor N3000 Series
<b>Network</b>	10/100/1000MbpsAdaptive,RTL8111F
<b>Extendable</b>	WIFI+Bluetooth Module (M.2 PCIE)
<b>OS Support</b>	Windows (Not include XP) & Linux

<b>I/O Ports</b>	2*USB2.0、4*USB3.0、1*VGA、2*HDMI、2*RJ45、1*COM、1*Type-C、1*DC、1*MIC-IN、1*LINE-OUT
<b>Internal I/O Ports</b>	1*COM 、1*SATA 、1* F_Audio、1*FP

## BIOS Function

<b>Display Mode</b>	1080P/ Support Triple display (Duplicate mode, Extend mode) Max Resolution(VGA): 1920*1080@60Hz; Max Resolution(HDMI): 1920*1080@60Hz
<b>Boot Mode</b>	PXE / Auto-power-on / Wake-on-LAN
<b>Intel Virtualization</b>	Support VT-x, Not support VT-d
<b>Intel Hyper-Threading</b>	Not support
<b>Working Environment</b>	Temperature: -10~60 °C Relative Humidity: 0~95% (No Condensation)
<b>Working Voltage</b>	DC 12V - 3A
<b>Static Electricity</b>	Contact discharge 2K, Air discharge 6K
<b>Storage Environment</b>	Temperature: -10~60 °C Relative Humidity: 0~95% (No Condensation)

# MINI PC K6-F13H

Intel Celeron N3150

I/O Port

01	Power on/off	02	USB3.0*2	03	USB3.0*2
04	RESET	05	Type-C	06	MIC
07	COM	08	SPK	09	USB2.0*2
10	RJ45	11	RJ45	12	VGA
13	HDMI*2	14	DC 12V input		

**Size** L 133.8mm\*W 126.6mm\*H 36.5mm

**Weight** Net : 0.6kg Gross : 1.3kg



Specification

<b>Features</b>	Using aluminum alloy shell, unique ice fin appearance design, fanless and more quiet		
<b>Heat Dissipation</b>	Fanless Passive Cooling		
<b>Bracket</b>	Dedicated bracket; Support VESA bracket		
<b>Packing Box</b>	Kraft paper color box + Anti-fall corrugated outer box		
<b>Packing List</b>	Power Adapter * 1	Power Cable* 1	VESA Bracket * 1
	User Manual * 1	QC Card * 1	Screws*1